

BSA

9 kHz ... 100 MHz

Solid State

Standard Models

Model	Frequency Range	Output Power P_N min W	Gain min / typ dB	Harmonics 2nd / 3rd dBc	Line Power W	Dimensions (H, D) 19"-System	Weight kg
BSA 0110-100	9 kHz ... 100 MHz	100	50 / 52 $\pm$ 2	20 / 20	400	4 HU, 550 mm	21
BSA 0110-175	9 kHz ... 100 MHz	175	52.4 / 55 $\pm$ 2	20 / 20	800	4 HU, 550 mm	32
BSA 0110-350	9 kHz ... 100 MHz	350	55.4 / 58 $\pm$ 2	20 / 20	1500	5 HU, 630 mm	45
BSA 0110-500	9 kHz ... 100 MHz	500	57 / 59 $\pm$ 2	20 / 20	3000	9 HU, 630 mm	90
BSA 0110-1000	9 kHz ... 100 MHz	1000	60 / 62 $\pm$ 2	20 / 20	6000	20 HU, 630 mm	190

Standard Specifications:

Input Power:	0 dBm (1 mW) max.
Overdrive Protection:	up to +10 dBm for no damage
Input Impedance:	50 Ohm nominal
Output Impedance:	50 Ohm nominal
Input VSWR:	<2:1 typ.
Load VSWR:	2:1 max. for P_N -0.5 dB; infinite for no damage
Spurious (at P_N):	-50 dBc typ.(excluding harmonics)
Class of Operation:	A-linear

General:

RF Input:	N-f; standard on rear panel
RF Output:	N-f; standard on rear panel

Mains Supply:	Line Power: <1000 W 100 ... 240 V AC $\pm 10\%$ / 47 ... 63 Hz Line Power: 1000 ... 3000 W 200 ... 240 V AC $\pm 10\%$ / 47 ... 63 Hz Line Power: >3000 W 3x 400 V AC $\pm 10\%$ / 47 ... 63 Hz
Elapsed Time Meter:	via status display
Ambient Temperature:	0 ... +45 °C
Storage Temperature:	-20 ... +85 °C
Relative Humidity:	up to 95% (non-condensing)
Operating Altitude:	up to 2000 m above sea level
Vibration and Shock:	MIL-STD-810 F
Cooling:	forced air with integral blower, air intake from front air exhaust at rear

Options:

A) RF Monitor Outputs	F) Gain Adjustment
B) External Dual Directional Coupler	H) DC-Supply
C) IEEE-488.2 GPIB Remote Control	R) RS-232C Remote Control
D) Front Panel RF-Connectors	U) USB Remote Control
E) Power Indication (digital)	

Specifications are subject to change without notice

BONN Elektronik GmbH – BSA 9 kHz ... 100 MHz



Rudolf-Diesel-Str.18 · D-85521 Ottobrunn · Tel +49 (0)89/608 754-0 · Fax +49 (0)89/608 754-99
email: info@bonn-elektronik.com · home: www.bonn-elektronik.com